

How to upgrade firmware:

Environment:

- Windows XP, Vista, Win 7
- 32 bit, 64bits
- Administrator mode

Notice:


- If OS is windows 7/Vista, you need to change the system notice setting. E.g, if you are using a windows 7, please log into control panel --- User Accounts --- Change User Account Control settings, then set notification rule block to "Never notify", click "OK".

Steps:


1 Run the firmware update exe file (USB3 Hub FW Upgrade Tool Setup Wizard), click next till Finish. Then please restart your computer to complete the installation.

2 Put the bin file you wanted for the hub into the "Bin" folder as the path below: C:\Program Files \USB3 Hub FW Upgrade Tool\Bin

PS. The 1st bin file in the "Bin" folder will take effect if there's more than 1 bin file there.




3 Run the Usb 3 Hub FW Upgrade.exe from Start, click Scan Devices, ensure the hub is connected.



4 Click Start Upgrade, then the Firmware will update automatically.



5 When the upgrading is done, you will see



6 Unplug and re-plug the power adapter for hub, press Scan Devices, double confirm the Firmware version as **V8.80**

